

Operator Related Problems

(Total 15 questions)

SL	Problem statement	Difficulty levels						
1.	<p>Program that will take two numbers X and Y as inputs, then calculate and print the values of their addition, subtraction, multiplication, division (quotient and remainder).</p> <table border="1"> <thead> <tr> <th>Sample input (X,Y)</th><th>Sample output</th></tr> </thead> <tbody> <tr> <td>5 10</td><td> Addition: 15 Subtraction: -5 Multiplication: 50 Quotient : 0 Reminder: 5 </td></tr> <tr> <td>-5 10.5</td><td> Addition: 5.5 Subtraction: -15.5 Multiplication: -52.5 Quotient: 0 Reminder: -48 </td></tr> </tbody> </table> <div style="border: 1px solid black; padding: 10px; margin-top: 10px;"> <ul style="list-style-type: none"> ❖ $-14 \% 3 = -2$ ❖ $-14 \% -3 = -2$ ❖ $14 \% -3 = 2$ </div>	Sample input (X,Y)	Sample output	5 10	Addition: 15 Subtraction: -5 Multiplication: 50 Quotient : 0 Reminder: 5	-5 10.5	Addition: 5.5 Subtraction: -15.5 Multiplication: -52.5 Quotient: 0 Reminder: -48	*
Sample input (X,Y)	Sample output							
5 10	Addition: 15 Subtraction: -5 Multiplication: 50 Quotient : 0 Reminder: 5							
-5 10.5	Addition: 5.5 Subtraction: -15.5 Multiplication: -52.5 Quotient: 0 Reminder: -48							
2.	<p>Program that will calculate the area of a circle having radius r.</p> $\text{Area, } A = 2 * \text{Pi} * r$ <table border="1"> <thead> <tr> <th>Sample input (r)</th><th>Sample output</th></tr> </thead> <tbody> <tr> <td>5</td><td>Area: 31.4</td></tr> <tr> <td>10.5</td><td>Area: 65.94</td></tr> </tbody> </table>	Sample input (r)	Sample output	5	Area: 31.4	10.5	Area: 65.94	*
Sample input (r)	Sample output							
5	Area: 31.4							
10.5	Area: 65.94							
3.	<p>Program that will take two numbers (a, b) as inputs and compute the value of the equation – (Without using math.h)</p> $X = (3.31 * a^2 + 2.01 * b^3) / (7.16 * b^2 + 2.01 * a^3)$ <table border="1"> <thead> <tr> <th>Sample input (a, b)</th><th>Sample output</th></tr> </thead> <tbody> <tr> <td>5 10.5</td><td>$X = 2.315475$</td></tr> <tr> <td>100 -250</td><td>$X = -12.766287$</td></tr> </tbody> </table>	Sample input (a, b)	Sample output	5 10.5	$X = 2.315475$	100 -250	$X = -12.766287$	*
Sample input (a, b)	Sample output							
5 10.5	$X = 2.315475$							
100 -250	$X = -12.766287$							

4.	<p>Program that will increment and decrement a number X by 1 inside the <i>printf</i> function. (Use ++ and -- operators)</p> <table border="1" data-bbox="187 211 1354 570"> <thead> <tr> <th data-bbox="187 211 783 253">Sample input(X)</th><th data-bbox="783 211 1354 253">Sample output</th></tr> </thead> <tbody> <tr> <td data-bbox="187 253 783 422">5</td><td data-bbox="783 253 1354 422"> X++ : 5 ++X : 6 X-- : 5 --X : 4 </td></tr> <tr> <td data-bbox="187 422 783 570">-5</td><td data-bbox="783 422 1354 570"> X++ : -5 ++X : -4 X-- : -5 --X : -6 </td></tr> </tbody> </table>	Sample input(X)	Sample output	5	X++ : 5 ++X : 6 X-- : 5 --X : 4	-5	X++ : -5 ++X : -4 X-- : -5 --X : -6	**
Sample input(X)	Sample output							
5	X++ : 5 ++X : 6 X-- : 5 --X : 4							
-5	X++ : -5 ++X : -4 X-- : -5 --X : -6							
5.	<p>Program that will increment and decrement a number X by Y. (Use += and -= operators)</p> <table border="1" data-bbox="187 718 1354 929"> <thead> <tr> <th data-bbox="187 718 783 760">Sample input(X,Y)</th><th data-bbox="783 718 1354 760">Sample output</th></tr> </thead> <tbody> <tr> <td data-bbox="187 760 783 844">5 10</td><td data-bbox="783 760 1354 844"> Incremented Value: 10 Decrement Value: -5 </td></tr> <tr> <td data-bbox="187 844 783 929">-5 5</td><td data-bbox="783 844 1354 929"> Incremented Value: 0 Decrement Value: -10 </td></tr> </tbody> </table>	Sample input(X,Y)	Sample output	5 10	Incremented Value: 10 Decrement Value: -5	-5 5	Incremented Value: 0 Decrement Value: -10	*
Sample input(X,Y)	Sample output							
5 10	Incremented Value: 10 Decrement Value: -5							
-5 5	Incremented Value: 0 Decrement Value: -10							
6.	<p>Program that will multiply and divide a number X by Y. (Use *= and /= operators)</p> <table border="1" data-bbox="187 1087 1354 1298"> <thead> <tr> <th data-bbox="187 1087 783 1129">Sample input(X,Y)</th><th data-bbox="783 1087 1354 1129">Sample output</th></tr> </thead> <tbody> <tr> <td data-bbox="187 1129 783 1214">56 10</td><td data-bbox="783 1129 1354 1214"> Multiplication: 560 Division: 5 </td></tr> <tr> <td data-bbox="187 1214 783 1298">-56 -10</td><td data-bbox="783 1214 1354 1298"> Multiplication: 560 Division: 5 </td></tr> </tbody> </table>	Sample input(X,Y)	Sample output	56 10	Multiplication: 560 Division: 5	-56 -10	Multiplication: 560 Division: 5	*
Sample input(X,Y)	Sample output							
56 10	Multiplication: 560 Division: 5							
-56 -10	Multiplication: 560 Division: 5							
7.	<p>Program that will declare and initialize an integer and a floating point number. Then it will perform floating to integer and integer to floating conversions using</p> <ul style="list-style-type: none"> (a) Assignment operation (b) Type casting <table border="1" data-bbox="187 1552 1354 1763"> <thead> <tr> <th data-bbox="187 1552 538 1594">Sample input</th><th data-bbox="538 1552 1354 1594">Sample output</th></tr> </thead> <tbody> <tr> <td data-bbox="187 1594 538 1763">-150 123.125</td><td data-bbox="538 1594 1354 1763"> Assignment: 123.125000 assigned to an int produces 123 Assignment: -150 assigned to a float produces -150.000000 Type Casting: (float) -150 produces -150.000000 Type Casting: (int) 123.125 produces -123 </td></tr> </tbody> </table>	Sample input	Sample output	-150 123.125	Assignment: 123.125000 assigned to an int produces 123 Assignment: -150 assigned to a float produces -150.000000 Type Casting: (float) -150 produces -150.000000 Type Casting: (int) 123.125 produces -123	**		
Sample input	Sample output							
-150 123.125	Assignment: 123.125000 assigned to an int produces 123 Assignment: -150 assigned to a float produces -150.000000 Type Casting: (float) -150 produces -150.000000 Type Casting: (int) 123.125 produces -123							

8.	<p>Program that will take two numbers as inputs and print the maximum value. (Using conditional operator - ?)</p> <table border="1" data-bbox="187 211 1362 348"> <thead> <tr> <th data-bbox="187 211 775 264">Sample input (x, y)</th><th data-bbox="775 211 1362 264">Sample output</th></tr> </thead> <tbody> <tr> <td data-bbox="187 264 775 306">20 100</td><td data-bbox="775 264 1362 306">Max: 100</td></tr> <tr> <td data-bbox="187 306 775 348">50 -20</td><td data-bbox="775 306 1362 348">Max: 50</td></tr> </tbody> </table>	Sample input (x, y)	Sample output	20 100	Max: 100	50 -20	Max: 50	**
Sample input (x, y)	Sample output							
20 100	Max: 100							
50 -20	Max: 50							
9.	<p>Program that will evaluate the following equations -</p> $X = a - b / 3 + c * 2 - 1$ $Y = a - (b / (3 + c) * 2) - 1$ $Z = a - ((b / 3) + c * 2) - 1$ <table border="1" data-bbox="187 601 1362 770"> <thead> <tr> <th data-bbox="187 601 775 654">Sample input (a, b, c)</th><th data-bbox="775 601 1362 654">Sample output</th></tr> </thead> <tbody> <tr> <td data-bbox="187 654 775 770">9 12 3</td><td data-bbox="775 654 1362 770">X = 10 Y = 4 Z = -1</td></tr> </tbody> </table>	Sample input (a, b, c)	Sample output	9 12 3	X = 10 Y = 4 Z = -1	*		
Sample input (a, b, c)	Sample output							
9 12 3	X = 10 Y = 4 Z = -1							
10.	<p>Program that will take a, b & c as inputs and decide if the statements are True (1) or False (0)</p> <p>a) $(a + b) \leq 80$ b) $!(a + b)$ c) $c! = 0$</p> <table border="1" data-bbox="187 1119 1362 1277"> <thead> <tr> <th data-bbox="187 1119 775 1172">Sample input (a, b, c)</th><th data-bbox="775 1119 1362 1172">Sample output</th></tr> </thead> <tbody> <tr> <td data-bbox="187 1172 775 1277">10 -10 0</td><td data-bbox="775 1172 1362 1277">a) 1 b) 1 c) 0</td></tr> </tbody> </table>	Sample input (a, b, c)	Sample output	10 -10 0	a) 1 b) 1 c) 0	**		
Sample input (a, b, c)	Sample output							
10 -10 0	a) 1 b) 1 c) 0							
11.	<p>Program that will take a, b & c as inputs and decide if the statements are True (1) or False (0)</p> <p>1) $(a + b) \leq 80 \ \&& \ c \geq 0$ 2) $(a - b) == 0 \ \mid\mid \ c! = 0$ 3) $a! = b \ \mid\mid \ !(b < c) \ \&& \ c > 0$ 4) $(a! = b \ \mid\mid \ !(b < c)) \ \&& \ c > 0$</p> <table border="1" data-bbox="187 1657 1362 1869"> <thead> <tr> <th data-bbox="187 1657 775 1710">Sample input (a, b, c)</th><th data-bbox="775 1657 1362 1710">Sample output</th></tr> </thead> <tbody> <tr> <td data-bbox="187 1710 775 1869">10 -10 0</td><td data-bbox="775 1710 1362 1869">1) 0 2) 1 3) 1 4) 0</td></tr> </tbody> </table>	Sample input (a, b, c)	Sample output	10 -10 0	1) 0 2) 1 3) 1 4) 0	***		
Sample input (a, b, c)	Sample output							
10 -10 0	1) 0 2) 1 3) 1 4) 0							

12.	<p>Program that will take calculate the roots of a quadratic equation ($a.x^2 + b.x + c = 0$) from the formula, (here, dot (.) stands for multiplication) -</p> $root = \frac{-b \pm \sqrt{b^2 - 4.a.c}}{2.a}$ <table border="1"> <thead> <tr> <th>Sample input (a, b, c)</th><th>Sample output</th></tr> </thead> <tbody> <tr> <td>2 4 -16</td><td>2.00 -4.00</td></tr> <tr> <td>1 2 3</td><td>Imaginary</td></tr> </tbody> </table>	Sample input (a, b, c)	Sample output	2 4 -16	2.00 -4.00	1 2 3	Imaginary	***		
Sample input (a, b, c)	Sample output									
2 4 -16	2.00 -4.00									
1 2 3	Imaginary									
13.	<p>Program that will evaluate the equation</p> $2\cos^2 x - \sqrt{3} \sin x + \log \frac{x}{2}$ <p>; where $1 \leq x \leq 180$ [No checking needed]</p> <table border="1"> <thead> <tr> <th>Sample input (x)</th><th>Sample output</th></tr> </thead> <tbody> <tr> <td>30</td><td>1.810066</td></tr> <tr> <td>120</td><td>0.778151</td></tr> <tr> <td>180</td><td>3.954243</td></tr> </tbody> </table>	Sample input (x)	Sample output	30	1.810066	120	0.778151	180	3.954243	***
Sample input (x)	Sample output									
30	1.810066									
120	0.778151									
180	3.954243									
14.	<p>Program that will take a floating point number X as input and evaluate A,B,C where-</p> <p>A = Value when X is rounded up to the nearest integer B = Value when X is rounded down to the nearest integer C = Absolute value of X</p> <table border="1"> <thead> <tr> <th>Sample input(X)</th><th>Sample output</th></tr> </thead> <tbody> <tr> <td>10.6</td><td>A = 11, B = 10, C = 10.6</td></tr> <tr> <td>-77.9</td><td>A = 78, B = 77, C = 77.9</td></tr> </tbody> </table>	Sample input(X)	Sample output	10.6	A = 11, B = 10, C = 10.6	-77.9	A = 78, B = 77, C = 77.9	**		
Sample input(X)	Sample output									
10.6	A = 11, B = 10, C = 10.6									
-77.9	A = 78, B = 77, C = 77.9									
15.	<p>Program to find size of int, float, double and char of the system.</p> <table border="1"> <thead> <tr> <th>Sample input</th><th>Sample output</th></tr> </thead> <tbody> <tr> <td></td><td> Size of int in byte(s) = 4 Size of float in byte(s) = 4 Size of double in byte(s) = 8 Size of char in byte(s) = 1 </td></tr> </tbody> </table>	Sample input	Sample output		Size of int in byte(s) = 4 Size of float in byte(s) = 4 Size of double in byte(s) = 8 Size of char in byte(s) = 1	**				
Sample input	Sample output									
	Size of int in byte(s) = 4 Size of float in byte(s) = 4 Size of double in byte(s) = 8 Size of char in byte(s) = 1									