

Loop related problems (total 20 questions)

SL	Problem statement	Difficulty levels														
1.	<p>Write a program (WAP) that will print following series upto N^{th} terms.</p> <p style="text-align: center;">1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14,</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th style="text-align: center;"><i>Sample input</i></th><th style="text-align: center;"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td style="text-align: center;">2</td><td style="text-align: center;">1, 2</td></tr> <tr> <td style="text-align: center;">5</td><td style="text-align: center;">1, 2, 3, 4, 5</td></tr> <tr> <td style="text-align: center;">11</td><td style="text-align: center;">1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	2	1, 2	5	1, 2, 3, 4, 5	11	1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11	*						
<i>Sample input</i>	<i>Sample output</i>															
2	1, 2															
5	1, 2, 3, 4, 5															
11	1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11															
2.	<p>Write a program (WAP) that will print following series upto N^{th} terms.</p> <p style="text-align: center;">1, 3, 5, 7, 9, 11, 13, 15, 17, 19, 21, 23, 25, 27, 29, 31</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th style="text-align: center;"><i>Sample input</i></th><th style="text-align: center;"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td style="text-align: center;">2</td><td style="text-align: center;">1, 3</td></tr> <tr> <td style="text-align: center;">5</td><td style="text-align: center;">1, 3, 5, 7, 9</td></tr> <tr> <td style="text-align: center;">11</td><td style="text-align: center;">1, 3, 5, 7, 9, 11, 13, 15, 17, 19, 21</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	2	1, 3	5	1, 3, 5, 7, 9	11	1, 3, 5, 7, 9, 11, 13, 15, 17, 19, 21	*						
<i>Sample input</i>	<i>Sample output</i>															
2	1, 3															
5	1, 3, 5, 7, 9															
11	1, 3, 5, 7, 9, 11, 13, 15, 17, 19, 21															
3.	<p>Write a program (WAP) that will print following series upto N^{th} terms.</p> <p style="text-align: center;">1, 0, 1, 0, 1, 0, 1, 0, 1, 0, 1, 0, 1, 0, 1,</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th style="text-align: center;"><i>Sample input</i></th><th style="text-align: center;"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td style="text-align: center;">1</td><td style="text-align: center;">1</td></tr> <tr> <td style="text-align: center;">2</td><td style="text-align: center;">1, 0</td></tr> <tr> <td style="text-align: center;">3</td><td style="text-align: center;">1, 0, 1</td></tr> <tr> <td style="text-align: center;">4</td><td style="text-align: center;">1, 0, 1, 0</td></tr> <tr> <td style="text-align: center;">7</td><td style="text-align: center;">1, 0, 1, 0, 1, 0, 1</td></tr> <tr> <td style="text-align: center;">13</td><td style="text-align: center;">1, 0, 1, 0, 1, 0, 1, 0, 1, 0, 1, 0, 1</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	1	1	2	1, 0	3	1, 0, 1	4	1, 0, 1, 0	7	1, 0, 1, 0, 1, 0, 1	13	1, 0, 1, 0, 1, 0, 1, 0, 1, 0, 1, 0, 1	**
<i>Sample input</i>	<i>Sample output</i>															
1	1															
2	1, 0															
3	1, 0, 1															
4	1, 0, 1, 0															
7	1, 0, 1, 0, 1, 0, 1															
13	1, 0, 1, 0, 1, 0, 1, 0, 1, 0, 1, 0, 1															
4.	<p>Write a program (WAP) that will take N numbers as inputs and compute their average.</p> <p>(Restriction: Without using any array)</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th style="text-align: center;"><i>Sample input</i></th><th style="text-align: center;"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td style="text-align: center;">3 10 20 30.5</td><td style="text-align: center;">AVG of 3 inputs: 20.166667</td></tr> <tr> <td style="text-align: center;">2 22.4 11.1</td><td style="text-align: center;">AVG of 2 inputs: 16.750000</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	3 10 20 30.5	AVG of 3 inputs: 20.166667	2 22.4 11.1	AVG of 2 inputs: 16.750000	*								
<i>Sample input</i>	<i>Sample output</i>															
3 10 20 30.5	AVG of 3 inputs: 20.166667															
2 22.4 11.1	AVG of 2 inputs: 16.750000															

5.	<p>Write a program (WAP) that will take two numbers X and Y as inputs. Then it will print the square of X and increment (if X<Y) or decrement (if X>Y) X by 1, until X reaches Y. If and when X is equal to Y, the program prints “Reached!”</p> <table border="1" data-bbox="192 264 1346 432"> <thead> <tr> <th data-bbox="192 264 775 306"><i>Sample input(X,Y)</i></th><th data-bbox="775 264 1346 306"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="192 306 775 348">10 5</td><td data-bbox="775 306 1346 348">100, 81, 64, 49, 36, Reached!</td></tr> <tr> <td data-bbox="192 348 775 390">5 10</td><td data-bbox="775 348 1346 390">25, 36, 49, 64, 81, Reached!</td></tr> <tr> <td data-bbox="192 390 775 432">10 10</td><td data-bbox="775 390 1346 432">Reached!</td></tr> </tbody> </table>	<i>Sample input(X,Y)</i>	<i>Sample output</i>	10 5	100, 81, 64, 49, 36, Reached!	5 10	25, 36, 49, 64, 81, Reached!	10 10	Reached!	*
<i>Sample input(X,Y)</i>	<i>Sample output</i>									
10 5	100, 81, 64, 49, 36, Reached!									
5 10	25, 36, 49, 64, 81, Reached!									
10 10	Reached!									
6.	<p>Write a program (WAP) for the described scenario: Player-1 picks a number X and Player-2 has to guess that number within N tries. For each wrong guess by Player-2, the program prints “Wrong, N-1 Choice(s) Left!” If Player-2 at any time successfully guesses the number, the program prints “Right, Player-2 wins!” and <u>terminates right away</u>. Otherwise after the completion of N wrong tries, the program prints “Player-1 wins!” and halts.</p> <p>(Hint: Use break/continue)</p> <table border="1" data-bbox="192 908 1346 1383"> <thead> <tr> <th data-bbox="192 908 497 992"><i>Sample input (X,N,n1, n2,..,nN)</i></th><th data-bbox="497 908 1346 992"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="192 992 497 1119">5 3 12 8 5</td><td data-bbox="497 992 1346 1119">Wrong, 2 Choice(s) Left! Wrong, 1 Choice(s) Left! Right, Player-2 wins!</td></tr> <tr> <td data-bbox="192 1119 497 1246">100 5 50 100</td><td data-bbox="497 1119 1346 1246">Wrong, 4 Choice(s) Left! Right, Player-2 wins!</td></tr> <tr> <td data-bbox="192 1246 497 1383">20 3 12 8 5</td><td data-bbox="497 1246 1346 1383">Wrong, 2 Choice(s) Left! Wrong, 1 Choice(s) Left! Wrong, 0 Choice(s) Left! Player-1 wins!</td></tr> </tbody> </table>	<i>Sample input (X,N,n1, n2,..,nN)</i>	<i>Sample output</i>	5 3 12 8 5	Wrong, 2 Choice(s) Left! Wrong, 1 Choice(s) Left! Right, Player-2 wins!	100 5 50 100	Wrong, 4 Choice(s) Left! Right, Player-2 wins!	20 3 12 8 5	Wrong, 2 Choice(s) Left! Wrong, 1 Choice(s) Left! Wrong, 0 Choice(s) Left! Player-1 wins!	**
<i>Sample input (X,N,n1, n2,..,nN)</i>	<i>Sample output</i>									
5 3 12 8 5	Wrong, 2 Choice(s) Left! Wrong, 1 Choice(s) Left! Right, Player-2 wins!									
100 5 50 100	Wrong, 4 Choice(s) Left! Right, Player-2 wins!									
20 3 12 8 5	Wrong, 2 Choice(s) Left! Wrong, 1 Choice(s) Left! Wrong, 0 Choice(s) Left! Player-1 wins!									
7.	<p>Write a program (WAP) that will run and show keyboard inputs until the user types an ‘A’ at the keyboard.</p> <table border="1" data-bbox="192 1594 1346 1784"> <thead> <tr> <th data-bbox="192 1594 775 1636"><i>Sample input</i></th><th data-bbox="775 1594 1346 1636"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="192 1636 775 1784">X 1 a A</td><td data-bbox="775 1636 1346 1784">Input 1: X Input 2: 1 Input 3: a</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	X 1 a A	Input 1: X Input 2: 1 Input 3: a	*				
<i>Sample input</i>	<i>Sample output</i>									
X 1 a A	Input 1: X Input 2: 1 Input 3: a									

8.	<p>Write a program (WAP) that will reverse the digits of an input integer.</p> <table border="1" data-bbox="192 206 1351 333"> <thead> <tr> <th data-bbox="192 206 780 255"><i>Sample input</i></th><th data-bbox="780 206 1351 255"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="192 255 780 297">13579</td><td data-bbox="780 255 1351 297">97531</td></tr> <tr> <td data-bbox="192 297 780 340">4321</td><td data-bbox="780 297 1351 340">1234</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	13579	97531	4321	1234	**																																												
<i>Sample input</i>	<i>Sample output</i>																																																			
13579	97531																																																			
4321	1234																																																			
9.	<p>Write a program (WAP) that will find the grade of N students. For each student, it will take the marks of his/her the attendance (on 5 marks), assignment (on 10 marks), class test (on 15 marks), midterm (on 50 marks), term final (on 100 marks). Then based on the tables shown below, the program will output his grade.</p> <table border="1" data-bbox="518 671 1029 897"> <tbody> <tr> <td data-bbox="518 671 975 720">Attendance (A)</td><td data-bbox="975 671 1029 720">5%</td></tr> <tr> <td data-bbox="518 720 975 768">Assignments (HW)</td><td data-bbox="975 720 1029 768">10%</td></tr> <tr> <td data-bbox="518 768 975 817">Class Tests (CT)</td><td data-bbox="975 768 1029 817">15%</td></tr> <tr> <td data-bbox="518 817 975 865">Midterm (MT)</td><td data-bbox="975 817 1029 865">30%</td></tr> <tr> <td data-bbox="518 865 975 897">Final (TF)</td><td data-bbox="975 865 1029 897">40%</td></tr> </tbody> </table> <table border="1" data-bbox="241 931 1307 1178"> <thead> <tr> <th data-bbox="241 931 393 979">Marks</th><th data-bbox="393 931 545 979">Letter Grade</th><th data-bbox="545 931 696 979">Marks</th><th data-bbox="696 931 848 979">Letter Grade</th><th data-bbox="848 931 1000 979">Marks</th><th data-bbox="1000 931 1152 979">Letter Grade</th></tr> </thead> <tbody> <tr> <td data-bbox="241 979 393 1028">90-100</td><td data-bbox="393 979 545 1028">A</td><td data-bbox="545 979 696 1028">70-73</td><td data-bbox="696 979 848 1028">C+</td><td data-bbox="848 979 1000 1028">Less than 55</td><td data-bbox="1000 979 1152 1028">F</td></tr> <tr> <td data-bbox="241 1028 393 1077">86-89</td><td data-bbox="393 1028 545 1077">A-</td><td data-bbox="545 1028 696 1077">66-69</td><td data-bbox="696 1028 848 1077">C</td><td data-bbox="848 1028 1000 1077"></td><td data-bbox="1000 1028 1152 1077"></td></tr> <tr> <td data-bbox="241 1077 393 1125">82-85</td><td data-bbox="393 1077 545 1125">B+</td><td data-bbox="545 1077 696 1125">62-65</td><td data-bbox="696 1077 848 1125">C-</td><td data-bbox="848 1077 1000 1125"></td><td data-bbox="1000 1077 1152 1125"></td></tr> <tr> <td data-bbox="241 1125 393 1174">78-81</td><td data-bbox="393 1125 545 1174">B</td><td data-bbox="545 1125 696 1174">58-61</td><td data-bbox="696 1125 848 1174">D+</td><td data-bbox="848 1125 1000 1174"></td><td data-bbox="1000 1125 1152 1174"></td></tr> <tr> <td data-bbox="241 1174 393 1222">74-77</td><td data-bbox="393 1174 545 1222">B-</td><td data-bbox="545 1174 696 1222">55-57</td><td data-bbox="696 1174 848 1222">D</td><td data-bbox="848 1174 1000 1222"></td><td data-bbox="1000 1174 1152 1222"></td></tr> </tbody> </table> <table border="1" data-bbox="192 1254 1356 1417"> <thead> <tr> <th data-bbox="192 1254 780 1303"><i>Sample input (A,HW,CT,MT,TF)</i></th><th data-bbox="780 1254 1356 1303"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="192 1303 780 1417">2 5 10 15 44.5 92.5 0 7.5 5 20 55.5</td><td data-bbox="780 1303 1356 1417">Student 1 : A Student 2 : F</td></tr> </tbody> </table>	Attendance (A)	5%	Assignments (HW)	10%	Class Tests (CT)	15%	Midterm (MT)	30%	Final (TF)	40%	Marks	Letter Grade	Marks	Letter Grade	Marks	Letter Grade	90-100	A	70-73	C+	Less than 55	F	86-89	A-	66-69	C			82-85	B+	62-65	C-			78-81	B	58-61	D+			74-77	B-	55-57	D			<i>Sample input (A,HW,CT,MT,TF)</i>	<i>Sample output</i>	2 5 10 15 44.5 92.5 0 7.5 5 20 55.5	Student 1 : A Student 2 : F	*
Attendance (A)	5%																																																			
Assignments (HW)	10%																																																			
Class Tests (CT)	15%																																																			
Midterm (MT)	30%																																																			
Final (TF)	40%																																																			
Marks	Letter Grade	Marks	Letter Grade	Marks	Letter Grade																																															
90-100	A	70-73	C+	Less than 55	F																																															
86-89	A-	66-69	C																																																	
82-85	B+	62-65	C-																																																	
78-81	B	58-61	D+																																																	
74-77	B-	55-57	D																																																	
<i>Sample input (A,HW,CT,MT,TF)</i>	<i>Sample output</i>																																																			
2 5 10 15 44.5 92.5 0 7.5 5 20 55.5	Student 1 : A Student 2 : F																																																			
10.	<p>Write a program (WAP) that will give the sum of first N^{th} terms for the following series.</p> $1, -2, 3, -4, 5, -6, 7, -8, 9, -10, 11, -12, 13, -14, \dots$ <table border="1" data-bbox="192 1649 1351 1812"> <thead> <tr> <th data-bbox="192 1649 780 1698"><i>Sample input</i></th><th data-bbox="780 1649 1351 1698"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="192 1698 780 1740">2</td><td data-bbox="780 1698 1351 1740">Result: -1</td></tr> <tr> <td data-bbox="192 1740 780 1782">3</td><td data-bbox="780 1740 1351 1782">Result: 2</td></tr> <tr> <td data-bbox="192 1782 780 1824">4</td><td data-bbox="780 1782 1351 1824">Result: -2</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	2	Result: -1	3	Result: 2	4	Result: -2	**																																										
<i>Sample input</i>	<i>Sample output</i>																																																			
2	Result: -1																																																			
3	Result: 2																																																			
4	Result: -2																																																			

11.	<p>Write a program (WAP) that will calculate the result for the first N^{th} terms of the following series. [In that series sum, dot sign (.) means multiplication]</p> $1^2.2+2^2.3+3^2.4+4^2.5+\dots$ <table border="1" data-bbox="187 264 1346 475"> <thead> <tr> <th data-bbox="187 264 775 306"><i>Sample input</i></th><th data-bbox="775 264 1346 306"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="187 306 775 348">2</td><td data-bbox="775 306 1346 348">Result: 14</td></tr> <tr> <td data-bbox="187 348 775 390">3</td><td data-bbox="775 348 1346 390">Result: 50</td></tr> <tr> <td data-bbox="187 390 775 432">4</td><td data-bbox="775 390 1346 432">Result: 130</td></tr> <tr> <td data-bbox="187 432 775 475">7</td><td data-bbox="775 432 1346 475">Result: 924</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	2	Result: 14	3	Result: 50	4	Result: 130	7	Result: 924	**
<i>Sample input</i>	<i>Sample output</i>											
2	Result: 14											
3	Result: 50											
4	Result: 130											
7	Result: 924											
12.	<p>Write a program (WAP) that will print Fibonacci series upto N^{th} terms.</p> $1,1,2,3,5,8,13,21, 34, 55, 89, \dots$ <table border="1" data-bbox="187 686 1346 897"> <thead> <tr> <th data-bbox="187 686 497 728"><i>Sample input</i></th><th data-bbox="497 686 1346 728"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="187 728 497 770">1</td><td data-bbox="497 728 1346 770">1</td></tr> <tr> <td data-bbox="187 770 497 813">2</td><td data-bbox="497 770 1346 813">1, 1</td></tr> <tr> <td data-bbox="187 813 497 855">4</td><td data-bbox="497 813 1346 855">1,1,2,3</td></tr> <tr> <td data-bbox="187 855 497 897">7</td><td data-bbox="497 855 1346 897">1,1,2,3,5,8,13</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	1	1	2	1, 1	4	1,1,2,3	7	1,1,2,3,5,8,13	**
<i>Sample input</i>	<i>Sample output</i>											
1	1											
2	1, 1											
4	1,1,2,3											
7	1,1,2,3,5,8,13											
13.	<p>Write a program (WAP) that will print the factorial ($N!$) of a given number N. Please see the sample input output.</p> <table border="1" data-bbox="187 1129 1346 1341"> <thead> <tr> <th data-bbox="187 1129 775 1172"><i>Sample input</i></th><th data-bbox="775 1129 1346 1172"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="187 1172 775 1214">1</td><td data-bbox="775 1172 1346 1214">1! = 1 = 1</td></tr> <tr> <td data-bbox="187 1214 775 1256">2</td><td data-bbox="775 1214 1346 1256">2! = 2 X 1 = 2</td></tr> <tr> <td data-bbox="187 1256 775 1298">3</td><td data-bbox="775 1256 1346 1298">3! = 3 X 2 X 1 = 6</td></tr> <tr> <td data-bbox="187 1298 775 1341">4</td><td data-bbox="775 1298 1346 1341">4! = 4 X 3 X 2 X 1 = 24</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	1	1! = 1 = 1	2	2! = 2 X 1 = 2	3	3! = 3 X 2 X 1 = 6	4	4! = 4 X 3 X 2 X 1 = 24	**
<i>Sample input</i>	<i>Sample output</i>											
1	1! = 1 = 1											
2	2! = 2 X 1 = 2											
3	3! = 3 X 2 X 1 = 6											
4	4! = 4 X 3 X 2 X 1 = 24											
14.	<p>Write a program (WAP) that will find ${}^n C_r$ where $n \geq r$; n and r are integers.</p> <table border="1" data-bbox="187 1488 1346 1700"> <thead> <tr> <th data-bbox="187 1488 497 1531"><i>Sample input</i></th><th data-bbox="497 1488 1346 1531"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="187 1531 497 1573">5 2</td><td data-bbox="497 1531 1346 1573">10</td></tr> <tr> <td data-bbox="187 1573 497 1615">10 3</td><td data-bbox="497 1573 1346 1615">120</td></tr> <tr> <td data-bbox="187 1615 497 1657">7 7</td><td data-bbox="497 1615 1346 1657">1</td></tr> <tr> <td data-bbox="187 1657 497 1700">6 1</td><td data-bbox="497 1657 1346 1700">6</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	5 2	10	10 3	120	7 7	1	6 1	6	**
<i>Sample input</i>	<i>Sample output</i>											
5 2	10											
10 3	120											
7 7	1											
6 1	6											

15.	<p>Write a program (WAP) that will find x^y (x to the power y) where x, y are positive integers.</p> <table border="1" data-bbox="187 168 1346 380"> <thead> <tr> <th data-bbox="187 168 489 221"><i>Sample input(x,y)</i></th><th data-bbox="489 168 1346 221"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="187 221 489 264">5 2</td><td data-bbox="489 221 1346 264">25</td></tr> <tr> <td data-bbox="187 264 489 306">2 0</td><td data-bbox="489 264 1346 306">1</td></tr> <tr> <td data-bbox="187 306 489 348">6 1</td><td data-bbox="489 306 1346 348">6</td></tr> <tr> <td data-bbox="187 348 489 380">0 5</td><td data-bbox="489 348 1346 380">0</td></tr> </tbody> </table>	<i>Sample input(x,y)</i>	<i>Sample output</i>	5 2	25	2 0	1	6 1	6	0 5	0	*		
<i>Sample input(x,y)</i>	<i>Sample output</i>													
5 2	25													
2 0	1													
6 1	6													
0 5	0													
16.	<p>WAP that will find the GCD (greatest common divisor) and LCM (least common multiple) of two positive integers.</p> <table border="1" data-bbox="187 570 1346 844"> <thead> <tr> <th data-bbox="187 570 489 623"><i>Sample input</i></th><th data-bbox="489 570 1346 623"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="187 623 489 696">5 7</td><td data-bbox="489 623 1346 696">GCD: 1 LCM: 35</td></tr> <tr> <td data-bbox="187 696 489 770">12 12</td><td data-bbox="489 696 1346 770">GCD: 12 LCM: 12</td></tr> <tr> <td data-bbox="187 770 489 844">12 32</td><td data-bbox="489 770 1346 844">GCD: 4 LCM: 96</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	5 7	GCD: 1 LCM: 35	12 12	GCD: 12 LCM: 12	12 32	GCD: 4 LCM: 96	**				
<i>Sample input</i>	<i>Sample output</i>													
5 7	GCD: 1 LCM: 35													
12 12	GCD: 12 LCM: 12													
12 32	GCD: 4 LCM: 96													
17.	<p>WAP that will determine whether a number is prime or not.</p> <table border="1" data-bbox="187 1056 1346 1288"> <thead> <tr> <th data-bbox="187 1056 489 1108"><i>Sample input</i></th><th data-bbox="489 1056 1346 1108"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="187 1108 489 1151">1</td><td data-bbox="489 1108 1346 1151">Not prime</td></tr> <tr> <td data-bbox="187 1151 489 1193">2</td><td data-bbox="489 1151 1346 1193">Prime</td></tr> <tr> <td data-bbox="187 1193 489 1235">11</td><td data-bbox="489 1193 1346 1235">Prime</td></tr> <tr> <td data-bbox="187 1235 489 1277">39</td><td data-bbox="489 1235 1346 1277">Not prime</td></tr> <tr> <td data-bbox="187 1277 489 1320">101</td><td data-bbox="489 1277 1346 1320">Prime</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	1	Not prime	2	Prime	11	Prime	39	Not prime	101	Prime	**
<i>Sample input</i>	<i>Sample output</i>													
1	Not prime													
2	Prime													
11	Prime													
39	Not prime													
101	Prime													
18.	<p>WAP that will determine whether an integer is palindrome number or not.</p> <table border="1" data-bbox="187 1478 1346 1710"> <thead> <tr> <th data-bbox="187 1478 489 1531"><i>Sample input</i></th><th data-bbox="489 1478 1346 1531"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="187 1531 489 1573">9</td><td data-bbox="489 1531 1346 1573">Yes</td></tr> <tr> <td data-bbox="187 1573 489 1615">91</td><td data-bbox="489 1573 1346 1615">No</td></tr> <tr> <td data-bbox="187 1615 489 1657">222</td><td data-bbox="489 1615 1346 1657">Yes</td></tr> <tr> <td data-bbox="187 1657 489 1700">12321</td><td data-bbox="489 1657 1346 1700">Yes</td></tr> <tr> <td data-bbox="187 1700 489 1742">110</td><td data-bbox="489 1700 1346 1742">No</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	9	Yes	91	No	222	Yes	12321	Yes	110	No	**
<i>Sample input</i>	<i>Sample output</i>													
9	Yes													
91	No													
222	Yes													
12321	Yes													
110	No													

19.	<p>WAP that will calculate following mathematical function for the input of x. Use only the series to solve the problem.</p> $\text{Sin}x = x - \frac{x^3}{3!} + \frac{x^5}{5!} - \frac{x^7}{7!} + \dots \dots \dots \infty$ <table border="1" data-bbox="186 340 1351 502"> <thead> <tr> <th data-bbox="186 340 491 382"><i>Sample input</i></th><th data-bbox="491 340 1351 382"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="186 382 491 424">1</td><td data-bbox="491 382 1351 424">0.841</td></tr> <tr> <td data-bbox="186 424 491 466">2</td><td data-bbox="491 424 1351 466">0.909</td></tr> <tr> <td data-bbox="186 466 491 508">3</td><td data-bbox="491 466 1351 508">0.141</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	1	0.841	2	0.909	3	0.141	***		
<i>Sample input</i>	<i>Sample output</i>											
1	0.841											
2	0.909											
3	0.141											
20.	<p>Write a program that takes an integer number n as input and find out the sum of the following series up to n terms.</p> $1 + 12 + 123 + 1234 + \dots \dots$ <table border="1" data-bbox="186 734 1351 946"> <thead> <tr> <th data-bbox="186 734 491 777"><i>Sample input</i></th><th data-bbox="491 734 1351 777"><i>Sample output</i></th></tr> </thead> <tbody> <tr> <td data-bbox="186 777 491 819">1</td><td data-bbox="491 777 1351 819">1</td></tr> <tr> <td data-bbox="186 819 491 861">2</td><td data-bbox="491 819 1351 861">13</td></tr> <tr> <td data-bbox="186 861 491 903">3</td><td data-bbox="491 861 1351 903">136</td></tr> <tr> <td data-bbox="186 903 491 946">4</td><td data-bbox="491 903 1351 946">1370</td></tr> </tbody> </table>	<i>Sample input</i>	<i>Sample output</i>	1	1	2	13	3	136	4	1370	**
<i>Sample input</i>	<i>Sample output</i>											
1	1											
2	13											
3	136											
4	1370											